

When using the Bogart Engineering SC2030 Solar Charger with the TM-2030 TriMetric meter, here's how to find the program values to put into the TM-2030 to properly charge your batteries. Go to Bogartengineering.com web site, then "Support," then "Get SC2030 Charging data."

Once you get this data (P1 through P21) here are step by step instructions for entering the data into the TM2030:

1. Press and hold **SELECT** button down until "P1" appears in display. It will take about 5 seconds. Then release. If you miss, just keep holding **SELECT** down and wait for the P1 to come around again. You should see P1 alternating with the P1 data value. To **change** P1 data skip to Step 3.
2. Push **SELECT** once to view the next program item. Push repeatedly until you get to one you wish to change.
3. **When you get to a program item you want to change:** first, **momentarily** push BOTH **SELECT** and **RESET** buttons. Three green lights should now flash on the meter, indicating that the value can be changed.
 - 3a. Push **RESET** to increase the numbers. Hold down to make them go up faster. When you get close to the correct value, stop and use short pushes to increase the display more slowly.
 - 3b. If you overshoot, or need to go **DOWN** to a lower value, keep pushing **RESET** until you get to the maximum (65.0 volts)—then it will go down to 10.0, and begin to increase from there. When satisfied with the number, push **SELECT** once.
4. Push **SELECT** again to go to the next program item. The remainder of settings may be changed the same way as for P1. (Step 3)
5. If you need to go back to a lower numbered program item, repeat step 1 to get back to P1 and advance from there.
6. When you are finished entering all values, push **SELECT** repeatedly until you get back to the regular display.